v-sol
Control Technology

# V-Sol Portable Solar Power Kit

# Portable Solar Power Kit

4500Mah High-Capacity

Hybrid Input

Bluetooth Speaker

FM Radio

Lighting Function

| Model | Parameter | Description |
|---|---|---|
| VSOL-PSG-001 | Rechargeable built-in battery | 3.7V 4500mAh Li-ion battery |
| | | 500 recycle times |
| | Micro USB input | DC5V |
| | USB output | DC5V |
| | Buld output | DC3V3W |
| | Solar panel | 6V2W |
| | Application range | Charge 3V~5V batteries |
| | Bluetooth NO. | BST-PSPK-001 |
| | Operating time | 1LED buld: 7hrs/2LED bulds: 4hrs/Front light: 11hrs/ Side light: 5hrs/FM&MP3: 8-10hrs |
| | Charging time | Adapter: 6hrs |
| | | 6V 2W Solar panel: 15hrs |
| | Features | Backup power,USB/TF music speaker, FM radio, usb charging mobile,can light 3PCS 3V lamps |



web: www.vsol-controls.com

Mail: info@vsol-controls.com

# Portable Solar Generator

| Model | VSOL-PSG-160W-F | VSOL-PSG-300W-F | VSOL-PSG-300W-F | VSOL-PSG-500W-F | VSOL-PSG-1000W-F |
|---|---|---|---|---|---|
| AC output power | 160W | 300W | 300W | 500W | 1000W |
| AC output: Volatge | 110V Fixed wave/220V Fixed wave | | 110V Pure sine wave/220V Pure sine wave | | |
| DC output | DC12V 2A(Ø5.5*2.1mm)/USB<br>5V2A /USB QC3.0 | | | | |
| Cell series connection | 3S | | | | |
| Rated capacity | 133 Wh | 222 Wh | 360Wh | 480Wh | 936Wh |
| Charging voltage | DC12.6-18V | | | | |
| Discharge cut-off voltage | 9V | | | | |
| Maximum charging current | 5A | | | 10A | |
| Cycle life | ≥ 1000 times @80%DOD, 25° C | | | | |
| Operating temperature | 0-50℃ | | | | |
| Product size(mm) | 200*105*165 | | 260*160*170 | | |
| Package dimensions(mm) | 290*145*215 | | 320*230*280 | | |
| Product gross weight(kg) | 2.5 | 2.9 | 5.5 | 6.8 | 8.8 |

vsol
Control Technology

# Contact Us

www.vsol-controls.com

info@vsol-controls.com

Made in Hungary